

Power Supplies

3-phase input voltage
10 A, 20 A



19,500.-



25,600.-

10 A	20 A																				
240 W	480 W																				
24 V DC (SELV)	24 V DC (SELV)																				
3x 400...500 V AC	3x 400...500 V AC																				
BAE PS-XA-3Y-24-100-006	BAE PS-XA-3Y-24-200-007																				
340...575 V AC/480...820 V DC	340...575 V AC/480...820 V DC																				
< 20 A	< 20 A																				
47...63 Hz	47...63 Hz																				
T2 A/600 V AC internal/phase	3.15 A/500 V AC internal/phase																				
22.5...28.5 V DC	22.5...28.5 V DC																				
±0.03 %/°C	±0.03 %/°C																				
100 mV	100 mV																				
> 20 ms	> 20 ms																				
Green LED	Green LED																				
Red LED	Red LED																				
90 %	90 %																				
Current limiter	Forward characteristic (C), deactivation within 3s, Restart after 30s (D)																				
> 30 kHz (typically)	> 75 kHz (typically)																				
3000 V AC	3000 V AC																				
100 MΩ	100 MΩ																				
< 1 s	< 1 s																				
-25...+71 °C	-25...+71 °C																				
-2.5 %/°C above +61 °C	-2.5 %/°C above +61 °C																				
Yes	Yes																				
IP 20	IP 20																				
DC OK output relay	DC OK output relay																				
Air convection	Air convection																				
Metal	Metal																				
1.1 kg	1.75 kg																				
CE, UL/cUL, TÜV	CE, UL/cUL, TÜV																				
<table border="1"> <tr><td>L</td><td>Input terminals</td></tr> <tr><td>PE</td><td>PE connection</td></tr> <tr><td>Vo -</td><td>Output terminal -</td></tr> <tr><td>Vo +</td><td>Output terminal +</td></tr> <tr><td>Rdy</td><td>Ready output</td></tr> </table>	L	Input terminals	PE	PE connection	Vo -	Output terminal -	Vo +	Output terminal +	Rdy	Ready output	<table border="1"> <tr><td>L</td><td>Input terminals</td></tr> <tr><td>PE</td><td>PE connection</td></tr> <tr><td>Vo -</td><td>Output terminal -</td></tr> <tr><td>Vo +</td><td>Output terminal +</td></tr> <tr><td>Rdy</td><td>Ready output</td></tr> </table>	L	Input terminals	PE	PE connection	Vo -	Output terminal -	Vo +	Output terminal +	Rdy	Ready output
L	Input terminals																				
PE	PE connection																				
Vo -	Output terminal -																				
Vo +	Output terminal +																				
Rdy	Ready output																				
L	Input terminals																				
PE	PE connection																				
Vo -	Output terminal -																				
Vo +	Output terminal +																				
Rdy	Ready output																				

