

## Power Supplies

3-phase input voltage

40 A

38,600.-



Output current	40 A								
Output power	960 W								
Output voltage	24 V DC (SELV)								
Input voltage	3x 400...500 V AC								
<b>Model (โมเดล)</b>	<b>BAE PS-XA-3Y-24-400-008</b>								
Input voltage range	340...575 V AC/480...820 V DC								
Inrush current	< 30 A								
Frequency range	47...63 Hz								
Input fuse	T5 A/500 V AC internal/phase								
Voltage adjustment range	22.5...28.5 V DC								
Temperature coefficient	±0.03 %/°C								
Ripple & noise	80 mV								
Holdup time	> 15 ms								
Status indicator DC ON	Green LED								
Status indicator DC LOW	Red LED								
Efficiency	92 %								
Response	Forward characteristic								
Switching frequency	> 50 kHz (typically)								
Isolation voltage	3000 V AC								
Isolation resistance	100 MΩ								
Turn-on delay	< 1 s								
Ambient temperature range	-25...+71 °C								
Derating	-3.5 %/°C above +61 °C								
Parallel mode	No								
Degree of protection as per IEC 60529	IP 20								
Ready output	No								
Cooling	Air convection								
Housing material	Metal								
Weight	3.2 kg								
Approvals	CE, UL/cUL, TÜV								
Wiring diagram	<table border="1" style="margin-left: 20px;"> <tr> <td>L</td> <td>Input terminals</td> </tr> <tr> <td>PE</td> <td>PE connection</td> </tr> <tr> <td>Vo -</td> <td>Output terminal -</td> </tr> <tr> <td>Vo +</td> <td>Output terminal +</td> </tr> </table>	L	Input terminals	PE	PE connection	Vo -	Output terminal -	Vo +	Output terminal +
L	Input terminals								
PE	PE connection								
Vo -	Output terminal -								
Vo +	Output terminal +								

\*SELV = Safety Extra Low Voltage

